



PTE-1 REX (Request to Exit) switch

Description

The new PTE-1 exit switch connects to any 12V access controller and provides users FAST SIMPLE door egress. It's small, lightweight, IP68-waterproof and has a simple Red/Green LED so users can see it's status. PTE-1 is included in ZKAccess door kits and can be purchased separately, as well.

Specification

- Dimensions: 114Lx70Wx16H(mm)
- Voltage: 12-24V
- Current: Standby 30mA, Operation: 70mA
- Output Contact: NO/NC/COM
- Current Rating: 1A @ 30VDC 0.5A @ 125VDC
- Waterproof Level: IP-68
- LED Status: Red: Standby, Green: Operation
- Wire color: Red: Positive, Black: Negative, Yellow: NC, White: COM, Green: NO

Wiring Diagram

 Red
 +
 12V DC

 Black

 Yellow
 NC

 White
 COM

 Green
 NO

ZKAccess

6 Kingsbridge Road, Unit 8, Fairfield, NJ 07004 Phone: (862) 505-2101 • Fax: (862) 204-5906 • sales@zkaccess.com • www.zkaccess.com

© Copyright 2015. ZKAccess. ZkAccess Logo is a registered trademark of ZKAccess or a relate company. All other product and company names mentioned are used for identification puposes only and may be the trademarks of their respective owners. All specifications are subject to change without notice. All rights reserved.

